

SPECIFICATION

Electronic Version 1.2.8

Stylesheet Version 1.0

[INSPECTION METHOD AND INSPECTION APPARATUS FOR SEMICONDUCTOR CIRCUIT]

Background of Invention

[0001] This invention relates to an inspection method and an inspection apparatus for semiconductor circuits with a plurality of semiconductor devices.

[0002] In production processes of various semiconductor devices consisting of circuit boards with a plurality of semiconductors mounted thereon, after assembly on a circuit board, the functioning of the semiconductor circuit board (workpiece) is inspected before it is transferred for shipment or movement to the next process. In performing the functional inspection, conventionally, the quality (defective or non-defective) of the workpiece has been determined by applying a working current for the semiconductor devices to the workpiece and a test is performed of whether each semiconductor device works or not.

[0003] The previous testing methods and apparatus do not in all instances offer a complete test of each semiconductor in the complete circuit. For example, in a semiconductor circuit with a plurality of semiconductors connected in parallel, if one device is disconnected due to an open breakage, the current flows into the other devices, so that no defect of the workpiece will be detected.

[0004] Recognizing this defect in the testing procedure, it has been proposed to apply a large current, over the normal limit value, to flow to detect the existence of a device subject to open breakage. However, if such a large current is inputted to the workpiece for inspection, when a defective device exists, the other normal devices may all be broken. This wastes the workpiece and decreases the yield rate, thus

increasing the piece price. Therefore, a one hundred percent inspection is dispensed with and a sampling inspection is performed for each lot. Obviously this results in insufficient reliability of the inspection.

[0005] In this case, even if deterioration of the working characteristic of the whole workpiece can be determined, it is impossible to determine which device is defective. On the other hand, if all the devices are inspected individually, a measuring apparatus with multiple minute inspection probes would be required. In such an event, the measuring apparatus would be a complicated one and expensive. Also, if the same loading voltage and current as in the condition of actual use are applied to each workpiece, the power supplying device and the loading device would be expensive.

[0006] In addition, if a device develops only a small electrostatic breakdown, it will still allow current to flow and would pass a conventional inspection method. In the case of such an electrostatic breakdown, the device will initially work, but deterioration of the broken-down device progresses during its use, causing malfunction of the whole circuit and decreasing the circuit life.

[0007] Therefore it is an object of this invention to provide an inspection method and an inspection apparatus for a semiconductor circuit that is capable of determining reliably the quality (defective or non-defective) of each device in the circuit even if a plurality of semiconductor devices are connected in parallel.

Summary of Invention

[0008] This invention is adapted to be embodied in an inspection method for a semiconductor circuit with a plurality of connected semiconductor devices. The method comprises the steps of applying an electrical load on the circuit, taking a photograph of the circuit with a thermographic camera to detect heat development of each semiconductor device in response to the applied load, and determining the quality of circuit and semiconductor devices based on the heat development.

[0009] In a preferred embodiment the temperature of the devices are measured at different points of time, and the quality (defective or non-defective) of the device is determined based on the temperature difference.

[0010] A further feature of the invention is adapted to be embodied in an inspection apparatus for a workpiece consisting of a semiconductor circuit with a plurality of connected semiconductor. The inspection apparatus comprises an apparatus body on which a workpiece to be inspected is set. A loading circuit for applying load corresponding to the condition of use to the workpiece is also provided along with a power source for supplying a working current to the workpiece through the loading circuit. A drive waveform generating circuit applies a drive signal to the workpiece. A thermographic camera takes photographs of the workpiece set on the apparatus body and an image processor receives signals from thermographic camera. Finally a control for controls the inspection apparatus to perform an inspection program.

Brief Description of Drawings

[0011] FIG. 1 is a schematic diagram of a semiconductor circuit inspection apparatus according to this invention and capable of performing an inspection operation in accordance with the invention.

[0012] FIG. 2 is a flowchart of an inspection method using the inspection apparatus of FIG. 1 and performing a method embodying the invention.

[0013] FIG. 3 is a time chart resulting from practicing the invention in accordance with the flowchart of FIG. 2.

[0014] FIG. 4 is a diagram in part similar to FIG. 3 but showing the results obtained in accordance with another embodiment of the invention.

[0015] FIG. 5 is a top plan view of an aluminum substrate to which a circuit tested by the present invention is applied.

[0016] FIG. 6 is a top plan view, in part similar to FIG. 5, but showing the chips and other components mounted on the aluminum substrate.

[0017] FIG. 7 is a side elevational view of the structure shown in FIG. 6.

[0018] FIG. 8 is top plan view of a motor control unit for an electric-powered vehicle incorporating a circuit tested in accordance with the invention.

[0019] FIG. 9 is a side elevational view of the motor control unit.

- [0020] FIG. 10 is an end elevational view of the motor control unit.
- [0021] FIG. 11 is a top plan view in part similar to FIG. 8, but with the potting compound removed and showing the contained components in solid lines.
- [0022] FIG. 12 is a side elevational view in part similar to FIG. 9, but with the potting compound removed and showing the contained components in solid lines.
- [0023] FIG. 13 is an end elevational view in part similar to FIG. 10, but with the potting compound removed and showing the contained components in solid lines.

Detailed Description

- [0024] Referring now in detail to the drawings and initially to FIG. 1, this shows a block diagram of a semiconductor circuit inspection apparatus constructed and operated according to an embodiment of this invention, indicated generally as 21. A workpiece namely a print circuit board, a specific example of which will be described later by reference to FIGS. 5-13, is indicated generally by the reference numeral 22. This workpiece 21 is set on an inspection apparatus body of a suitable type (not shown).
- [0025] A power source 23 is connected to the workpiece 22 through a loading circuit 24. The loading circuit 24 is a circuit in which load the same as or smaller than that in the condition of actual use, is applied to the workpiece 22 to test the performance or the characteristic of the workpiece 22.
- [0026] The power source 23 is connected to a control device 25. The control device 25 controls ON/OFF of the work controlling power source 23. The control device 25 is connected to the workpiece 22 through a drive waveform generating circuit 26. The drive waveform generating circuit 26 produces drive signal waveforms for switching semiconductors to be inspected, and applies the signal to the FETs of the workpiece 22.
- [0027] A thermographic camera 27 is provided above the workpiece 22 that is set on the apparatus body for taking photographs of the workpiece 22. The thermographic camera 27 takes photographs of the workpiece 22 and sends the heat image data to an image processor 28. The image processor 28 processes the heat image data and

executes temperature calculation or the like according to a program in the control device 25 or an input command signal. The result of this calculation is displayed on a monitor 29.

[0028] The preferred operational method of the invention will now be described by reference to FIG. 2 which is a flowchart of a semiconductor circuit inspection method using the inspection apparatus of FIG. 1. Reference will also be made to FIG. 3 which is a time and temperature chart. The program begins at the Step S1 in which the work controlling power source 23 (FIG. 1) is switched ON by hand or by an input command by a GPIB communication line or the like from the control device 25. At this moment or a little before this moment, photographs of individual devices (diodes 33 or FETs 34 FIGS. 5-7) of the workpiece 22 are taken with the thermographic camera 27 and the heat image data is sent to the image processor 28.

[0029] Then at the Step S2 a drive signal for switching semiconductor devices (FETs) from the drive waveform generating circuit 26 are ON. Operation of the step S2 may be performed at the same time as the step S1. As a result of the steps S1, S2, FETs 34 of the workpiece 22 are operated, raising their temperature. The steps S1 and S2 are performed at the time t_0 in the time diagram FIG. 3.

[0030] Following at the time t_1 at the Step S3 the temperature T_1 of each FET 34 of the workpiece 22 is measured by the image processor 28. Then at the Step S4 it is determined whether or not temperature T_1 is within the predetermined allowable range (within the temperature range in the normal operation). If it is, then at the Step S5 the temperature T_2 is measured at time t_2 from the heat image data.

[0031] At the Step S6 it is determined whether or not temperature T_2 is within the predetermined allowable range (within the temperature range in the normal operation). If at the Step S7 the temperature T_2 is normal, the drive signal applied to the workpiece 22 at time t_3 by the drive waveform generating circuit 26 is turned OFF. Then at the Step S8 following the step S7 or at the same time as in FIG. 3, the power source 23 is switched OFF. Thus, current supply for inspection is finished and the temperature of the device begins falling as shown in FIG. 3.

[0032] At the Step S9 the temperature difference $\Delta T = T_1 - T_2$ from the

temperature data T_1 , T_2 measured at the steps S3, S5, is calculated. Thus, temperature rise from t_1 to t_2 for each FET 34 is calculated. Then at the Step S10 it is determined whether or not the value ΔT of the temperature rise calculated at the step S9 is within the range of temperature rise of a normal device.

[0033] As a result of the quality (defective or non-defective) of the individual devices 34 being determined from the temperature difference as described above, compared with when determination is made only from T_1 or T_2 , the quality (defective or non-defective) of the individual devices can be determined based on the heat development characteristic of the device itself without influence of dispersion of the characteristics specific to individual devices or dispersion of the characteristics between all devices or lots in a production line and without influence of the temperature of the apparatus or the device, or the ambient temperature at the beginning of the measurement, enhancing reliability of the inspection.

[0034] Also, even if both T_1 and T_2 are normal at the steps S4 and S6, respectively, the difference ΔT can be out of the normal range depending on the criterion range of T_1 and T_2 at the steps S4, S6, therefore a step S10 should preferably be provided in addition to the steps S4, S6 for determination of T_1 , T_2 .

[0035] Then if the value ΔT is normal at the Step S11 an OK-sign is indicated on a monitor screen or other indicating lamp that inspection result of the workpiece is normal.

[0036] As implied above, if temperature T_1 or T_2 at the step S4 or S5 is out of the normal range, the program moves to the Step S12 where the drive waveform generating circuit 26 is switched OFF. Following the step S12 or at the same time, at the Step S13 the power source 23 is switched OFF. The aim of this step is to finish inspection because of the abnormality of the device found.

[0037] When it is determined that the workpiece is abnormal at the steps S4, S6 and S10, NG-sign is indicated on a monitor screen or other indicating lamp that the device is defective at the Step S14.

[0038] FIG. 4 is a diagram of another embodiment of this invention that employs a different method for determining that a device is defective. This method is based the

fact that a device is known to experience a temperature change when a current is inputted to the device. Also it is known that the temperature change is different when the resistance value is increased due to a defective solder joint of the device or voids generated in the solder joint.

[0039] Therefore in accordance with this method, the temperature change of each device is determined from temperature measurements taken at least at three points of time after an inspection current is inputted into the workpiece. The temperature change of each device is compared with a known temperature profile at the time of an electrostatic breakdown or void generation, to detect a defective device as well as the cause of the defect.

[0040] For example, and as shown in FIG. 4, relative to a normal device, a device whose solder joint has voids, has a more significant tendency of temperature rise in a temperature profile of upwardly convex shape when a drive signal is applied. Therefore, if temperatures are measured at different points of time more than twice, a general temperature profile can be obtained, and a device having a defective joint due to voids can be determined.

[0041] Regarding a device having an abnormal VGS-IV characteristic due to an electrostatic breakdown, since the general temperature profile is known, if temperatures of the devices are measured at different points of time more than twice to detect the temperature profile, a device having an electrostatic breakdown can be determined.

[0042] Referring now to FIGS. 5-13 these show a specific type of workpiece that can be tested with the apparatus and methods already described and show an embodiment where a substrate with mounted devices can be used as a motor control unit for driving an electric-powered vehicle.

[0043] As shown first in FIGS. 5-7, the device 22 is comprised of a conductor pattern of copper (not shown) is formed on an aluminum substrate 31 and coated with a resist 32. By patterning the resist 32, diode land patterns 33 and FET land patterns 34 constituting portions of a motor control circuit are formed. Output terminals 35a, 35b, and 35c of the control circuit are formed at three places on the aluminum

substrate 31 each having two output terminal holes 36, respectively. At the four corners of the aluminum substrate 31 are disposed mounting holes 37 for fixing a casing body as will be described later by reference to FIGS. 8-13. Further on the substrate is provided a gate resistance 38 forming a further component of the drive circuit.

[0044] Diodes 39 are soldered within the respective diode land patterns 33, and FETs 41 are soldered within the respective FET land patterns 34. Each diode 39 is respectively sealed or potted with a resin 42. Each FET 41 is sealed with resin 43 along with a connector 44. A commercially available liquid sealing material or resin of linear expansion coefficient of $(15 \text{ to } 30) \times 10^{-6} / ^\circ \text{C}$ can be selected to use as the potting material for sealing such diodes 39 and FETs 41. For example, sealing materials of linear expansion coefficient of $15 \times 10^{-6} / ^\circ \text{C}$ and $22 \times 10^{-6} / ^\circ \text{C}$ approximate to those of copper and aluminum respectively are easily available in the market.

[0045] Referring now to FIGS. 8-13, these figures show how a complete motor control unit incorporating the aluminum substrate 31 of FIGS. 5-7 can be constructed. The motor control unit, indicated generally by the reference numeral, 45 includes a drive control circuit configured of the aluminum substrate 31 as previously described by reference to FIGS. 4-6 in a casing body 46.

[0046] The casing body 46 is formed by the extrusion of a metallic material of aluminum or aluminum alloy. The casing body 46 is of a cylindrical shape with both ends open. A plurality of aligned parallel ribs 47 are formed to project from its outer circumferential surface. The ribs 47 increase the surface area of the casing body 46, resulting in the increase of heat radiation as well as the rigidity and strength of the casing body 46.

[0047] On the aluminum substrate 31 are mounted further devices constituting a drive control circuit such as an electrolytic capacitor 48 constituting a drive control circuit (FIG. 11). Also terminal attaching plates 49a, 49b, and 49c are connecting to the aforementioned output terminals 35a, 35b, and 36c. Each signal wire of the control circuit is connected through an electric cable 51 and a coupler 52 to switches and other drive or control parts on the vehicle side. Output terminals 53 passing through the aforementioned output terminal holes 37 project from the lower surface of the

aluminum substrate 31. Such an aluminum substrate 31 and the electronic parts mounted thereon are accommodated in the casing body 46 and sealed or potted with resin 54.

[0048] As described above, in this invention, image processing of the photographic data by a thermographic camera allows the heat development of individual semiconductor devices to be detected. Therefore, defects of individual devices such as disconnection due to breaks and abnormal heat development due to electrostatic breakdowns can be determined reliably. Of course those skilled in the art will readily perceive that the foregoing description is of preferred embodiments of the test methods and apparatus and that various changes and modifications may be made without departing from the spirit and scope of the invention as defined by the appended claims.

0048
0049
0050
0051
0052
0053
0054
0055
0056
0057
0058
0059
0060
0061
0062
0063
0064
0065
0066
0067
0068
0069
0070
0071
0072
0073
0074
0075
0076
0077
0078
0079
0080
0081
0082
0083
0084
0085
0086
0087
0088
0089
0090
0091
0092
0093
0094
0095
0096
0097
0098
0099
0100
0101
0102
0103
0104
0105
0106
0107
0108
0109
0110
0111
0112
0113
0114
0115
0116
0117
0118
0119
0120
0121
0122
0123
0124
0125
0126
0127
0128
0129
0130
0131
0132
0133
0134
0135
0136
0137
0138
0139
0140
0141
0142
0143
0144
0145
0146
0147
0148
0149
0150
0151
0152
0153
0154
0155
0156
0157
0158
0159
0160
0161
0162
0163
0164
0165
0166
0167
0168
0169
0170
0171
0172
0173
0174
0175
0176
0177
0178
0179
0180
0181
0182
0183
0184
0185
0186
0187
0188
0189
0190
0191
0192
0193
0194
0195
0196
0197
0198
0199
0200
0201
0202
0203
0204
0205
0206
0207
0208
0209
0210
0211
0212
0213
0214
0215
0216
0217
0218
0219
0220
0221
0222
0223
0224
0225
0226
0227
0228
0229
0230
0231
0232
0233
0234
0235
0236
0237
0238
0239
0240
0241
0242
0243
0244
0245
0246
0247
0248
0249
0250
0251
0252
0253
0254
0255
0256
0257
0258
0259
0260
0261
0262
0263
0264
0265
0266
0267
0268
0269
0270
0271
0272
0273
0274
0275
0276
0277
0278
0279
0280
0281
0282
0283
0284
0285
0286
0287
0288
0289
0290
0291
0292
0293
0294
0295
0296
0297
0298
0299
0300
0301
0302
0303
0304
0305
0306
0307
0308
0309
0310
0311
0312
0313
0314
0315
0316
0317
0318
0319
0320
0321
0322
0323
0324
0325
0326
0327
0328
0329
0330
0331
0332
0333
0334
0335
0336
0337
0338
0339
0340
0341
0342
0343
0344
0345
0346
0347
0348
0349
0350
0351
0352
0353
0354
0355
0356
0357
0358
0359
0360
0361
0362
0363
0364
0365
0366
0367
0368
0369
0370
0371
0372
0373
0374
0375
0376
0377
0378
0379
0380
0381
0382
0383
0384
0385
0386
0387
0388
0389
0390
0391
0392
0393
0394
0395
0396
0397
0398
0399
0400
0401
0402
0403
0404
0405
0406
0407
0408
0409
0410
0411
0412
0413
0414
0415
0416
0417
0418
0419
0420
0421
0422
0423
0424
0425
0426
0427
0428
0429
0430
0431
0432
0433
0434
0435
0436
0437
0438
0439
0440
0441
0442
0443
0444
0445
0446
0447
0448
0449
0450
0451
0452
0453
0454
0455
0456
0457
0458
0459
0460
0461
0462
0463
0464
0465
0466
0467
0468
0469
0470
0471
0472
0473
0474
0475
0476
0477
0478
0479
0480
0481
0482
0483
0484
0485
0486
0487
0488
0489
0490
0491
0492
0493
0494
0495
0496
0497
0498
0499
0500
0501
0502
0503
0504
0505
0506
0507
0508
0509
0510
0511
0512
0513
0514
0515
0516
0517
0518
0519
0520
0521
0522
0523
0524
0525
0526
0527
0528
0529
0530
0531
0532
0533
0534
0535
0536
0537
0538
0539
0540
0541
0542
0543
0544
0545
0546
0547
0548
0549
0550
0551
0552
0553
0554
0555
0556
0557
0558
0559
0560
0561
0562
0563
0564
0565
0566
0567
0568
0569
0570
0571
0572
0573
0574
0575
0576
0577
0578
0579
0580
0581
0582
0583
0584
0585
0586
0587
0588
0589
0590
0591
0592
0593
0594
0595
0596
0597
0598
0599
0600
0601
0602
0603
0604
0605
0606
0607
0608
0609
0610
0611
0612
0613
0614
0615
0616
0617
0618
0619
0620
0621
0622
0623
0624
0625
0626
0627
0628
0629
0630
0631
0632
0633
0634
0635
0636
0637
0638
0639
0640
0641
0642
0643
0644
0645
0646
0647
0648
0649
0650
0651
0652
0653
0654
0655
0656
0657
0658
0659
0660
0661
0662
0663
0664
0665
0666
0667
0668
0669
0670
0671
0672
0673
0674
0675
0676
0677
0678
0679
0680
0681
0682
0683
0684
0685
0686
0687
0688
0689
0690
0691
0692
0693
0694
0695
0696
0697
0698
0699
0700
0701
0702
0703
0704
0705
0706
0707
0708
0709
0710
0711
0712
0713
0714
0715
0716
0717
0718
0719
0720
0721
0722
0723
0724
0725
0726
0727
0728
0729
0730
0731
0732
0733
0734
0735
0736
0737
0738
0739
0740
0741
0742
0743
0744
0745
0746
0747
0748
0749
0750
0751
0752
0753
0754
0755
0756
0757
0758
0759
0760
0761
0762
0763
0764
0765
0766
0767
0768
0769
0770
0771
0772
0773
0774
0775
0776
0777
0778
0779
0780
0781
0782
0783
0784
0785
0786
0787
0788
0789
0790
0791
0792
0793
0794
0795
0796
0797
0798
0799
0800
0801
0802
0803
0804
0805
0806
0807
0808
0809
0810
0811
0812
0813
0814
0815
0816
0817
0818
0819
0820
0821
0822
0823
0824
0825
0826
0827
0828
0829
0830
0831
0832
0833
0834
0835
0836
0837
0838
0839
0840
0841
0842
0843
0844
0845
0846
0847
0848
0849
0850
0851
0852
0853
0854
0855
0856
0857
0858
0859
0860
0861
0862
0863
0864
0865
0866
0867
0868
0869
0870
0871
0872
0873
0874
0875
0876
0877
0878
0879
0880
0881
0882
0883
0884
0885
0886
0887
0888
0889
0890
0891
0892
0893
0894
0895
0896
0897
0898
0899
0900
0901
0902
0903
0904
0905
0906
0907
0908
0909
0910
0911
0912
0913
0914
0915
0916
0917
0918
0919
0920
0921
0922
0923
0924
0925
0926
0927
0928
0929
0930
0931
0932
0933
0934
0935
0936
0937
0938
0939
0940
0941
0942
0943
0944
0945
0946
0947
0948
0949
0950
0951
0952
0953
0954
0955
0956
0957
0958
0959
0960
0961
0962
0963
0964
0965
0966
0967
0968
0969
0970
0971
0972
0973
0974
0975
0976
0977
0978
0979
0980
0981
0982
0983
0984
0985
0986
0987
0988
0989
0990
0991
0992
0993
0994
0995
0996
0997
0998
0999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2